
SWITCHING AND AMPLIFIER APPLICATIONS

- Suitable for AF-Driver stages and low power output stages
- Complement to BC337/BC338

ABSOLUTE MAXIMUM RATINGS (T_A=25°C)

Characteristic	Symbol	Rating	Unit
Collector-Emitter Voltage : BC327 : BC328 Collector-Emitter Voltage : BC327 : BC327 : BC328 Emitter-Base Voltage Collector Current (DC) Collector Dissipation Junction Temperature Storage Temperature	VCES VCEO VEBO IC PC TJ TSTG	-50 -30 -45 -25 -5 -800 625 150 -55 ~ 150	∨ ∨ ∨ ∨ ∨ mA mW °C °C




ELECTRICAL CHARACTERISTICS (T_A=25°C)

Characteristic	Symbol	Test Conditions	Min	Тур	Max	Unit
Collector Emitter Breakdown Voltage	BV _{CEO}	I _C = -10mA, I _B =0	45			
: BC327			-45 -25			V
: BC328 Collector Emitter Breakdown Voltage	BV _{CES}	$I_{C} = -0.1 \text{mA}, I_{B} = 0$	-25			V
: BC327	- FCES		-50			V
: BC328			-30			V
Emitter Base Breakdown Voltage	BV _{EBO}	$I_E=-10mA$, $I_C=0$	-5			V
Collector Cut-off Current	I _{CES}					
: BC307		$V_{CE} = -45V, I_{B} = 0$		-2	-100	nA
: BC338		$V_{CE} = -25V, I_{B} = 0$		-2	-100	nA
DC Current Gain	h _{FE}	$V_{CE} = -1V, I_{C} = -100 \text{mA}$	100		630	
	h _{FE} 2	$V_{CE} = -1V, I_{C} = -30mA$	60			
Collector-Emitter Saturation Voltage	V _{CE} (sat)	I_{C} = -500mA, I_{B} = -50mA			-0.7	V
Base Emitter On Voltage	V _{BE} (on)	$V_{CE} = -1V, I_{C} = -300mA$			-1.2	V
Current Gain Bandwidth Product	f⊤	V_{CE} = -5V, I_{C} = -10mA		100		MHz
Collector Base Capacitance	C _{CBO}	V _{CB} = -10V, f=1MHz		12		pF


h_{FE} CLASSIFICATION


Classification	A	В	С
h _{FE}	100-250	160-400	250-630
h _{FE2}	60-	100-	170-
















TRADEMARKS

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

ACEXTM ISOPLANARTM
CoolFETTM MICROWIRETM

CROSSVOLTTM POPTM

E²CMOS[™] PowerTrench[™]

FACTTM QSTM

 $\begin{array}{lll} \mathsf{FACT} \ \mathsf{Quiet} \ \mathsf{Series^{\mathsf{TM}}} & \mathsf{Quiet} \ \mathsf{Series^{\mathsf{TM}}} \\ \mathsf{FAST}^{\otimes} & \mathsf{SuperSOT^{\mathsf{TM}}}\text{-}3 \\ \mathsf{FASTr^{\mathsf{TM}}} & \mathsf{SuperSOT^{\mathsf{TM}}}\text{-}6 \\ \mathsf{GTO^{\mathsf{TM}}} & \mathsf{SuperSOT^{\mathsf{TM}}}\text{-}8 \\ \mathsf{HiSeC^{\mathsf{TM}}} & \mathsf{TinyLogic^{\mathsf{TM}}} \end{array}$

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.

 A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

PRODUCT STATUS DEFINITIONS

Definition of Terms

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.